

Working Principle

A jamming device transmits on the same radio frequencies as the cell phone, disrupting the communication between the phone and the base station in the tower.

Application

- College
- Museum
- Court
- Petrol Station

Key Features

- Isolating Multi-frequency bands
- Isolating distance is adjustable
- Excellent performance of heat dispersion
- No harm to human body
- Much stabile working

Specifications

High Power Jammer



CR-JA09-4

High Power Series

| Models | CR-JA09-4 |
|---------------------------|--|
| Frequency | A)Tx frequency 869-894MHz B)Tx frequency 925-960MHz C)Tx frequency1930-1990MHz D) Tx frequency 2110-2155MHz Other frequency band can be customized |
| System | Analog (AMPS,TACS,NMT) Digital (GPRS,GSM, DCS,CDMA,PDC,TDMA,PHS,PCS,IDEN,W-CDMA,UMTS) |
| Power | 1watt per frequency band |
| Total Transimitting Power | 1-15 meters |
| Isolating Distance Range | AC 110V-220V |
| Weight | 2kg |
| Demension | 270(L)×245(W)×65(H) mm |
| Temperature Range | -10- +55 °C |
| Humidity | 5%--90% |

Package Set



Installation Instructions

- The product can be directly fixed on the wall or ceiling, the product surface temperature can reach 50 degrees Celsius, so please stay away from the low heat resistance.
- The best installation height: 1-2 meters.
- Connect the power plug directly to the power supply.